

 **MONSTER**[™]

**INDOOR/OUTDOOR
RGB+W**

**Water Resistant Multicolor + Multiwhite LED
Light Strip with Remote Control**

Operation Manual

MODEL MLB7-1037

V4.0 0523

Introduction

This 16.4ft(5m) Indoor/Outdoor LED Light Strip light is ideal for edge-lighting your deck or railings, or highlighting gardens and walkways, and gives you the look of professional lighting while enhancing the style and safety of your outdoor living spaces.

Features

- 16.4ft (5m) length - perfect for lighting decks, walkways, gardens, and more
- Waterproof LED light strip design is safe for both indoor and outdoor/wet environment use
- 6ft (1.8m) adapter cable easily reaches from outlet to the desired location
- Included mounting clips and screws for easy installation
- Multi-color/multi-white color changing and flash modes
- Remote control works up to 26 feet away

What's Included

- 16.4ft (5m) Indoor/Outdoor Led Light Strip
- Power Adapter with 6ft (1.8m) cord
- IR Remote Control with battery (1 x 3V battery, CR2025*)
- Mounting Clips x10 (screws x20)
- User Manual

Safety Instructions

Please read and understand all instructions before using this product. If damage is caused by failure to follow the instructions, this warranty is null and void.

WARNING: When using outdoor use products, basic safety precautions should always be followed to reduce the risk of fire, electric shock, and personal injury, including the following:

- Keep these instructions.
- Do not drop, puncture, or disassemble this product.
- This LED light strip is suitable for use in wet locations. Do not submerge the strip or the power supply unit in water.
- The plug on the power supply unit must be connected to a GFCI protected hooded flush type cover plate receptacle marked "Wet Location" while in use outdoors.
- This product has a polarized plug and will only fit in a polarized outlet. Do not attempt to defeat this safety feature. Do not alter the plug.
- Use only with an extension cord rated for outdoor use. Use only three-wire outdoor extension cords that have three-prong grounding plugs and grounding receptacles that accept the appliance's plug. Never use with an extension cord unless the plug can be fully inserted.


- Do not expose this product to open flames or use near fire.
- Do not use the product in a strong magnetic field.
- Use a clean, soft cloth to clean. Do not use any corrosive cleaners/oils to clean.
- Do not attempt to repair the device or open the unit as this will void the warranty.

NOTE: You cannot connect additional light strips to this product.

NOTE: If desired, you can cut the light strip to shorter lengths by cutting on the designated scissors marks. However, **IF THE PRODUCT HAS BEEN CUT IT WILL NO LONGER BE WATER PROOF.**

Get Started

- 1 Determine where you will install the Indoor/Outdoor LED Light Strip. Make sure the location is close enough to a power source for the cord to reach without becoming a tripping hazard.
- 2 Using the included mounting clips and screws, mount the Light Strip in the desired location. For best results place one clip approximately every 20", or 5 scissors marks, to secure the entire light strip evenly.



Note: Move some mounting clips closer to corners to better secure the strip around turns, use fewer on straight areas.

- 3 Once installed, connect the power adapter to a powered outlet. (Outdoors this must be a GFCI protected outlet.)
- 4 Remove the protective tab from the battery compartment of the remote. You are now ready to use your product.



TIP: If the power adapter doesn't reach to the ground from the outlet, use the keyhole hanger and a screw or nail to hang it.

MONSTER™



Operation Manual

MODEL MLB7-1037

V4.0 1021

Controls, at a Glance



IR Remote



IR Receiver
(on adapter housing)

①	ON/OFF	Turn the product on and off
②	MULTI-WHITE SELECTORS	Select from cool, soft, or warm white
③	MULTI-COLOR SELECTORS	Change the color to match your mood
④	FLASH	Flash color-changing mode
⑤	STROBE	Strobe color-changing mode
⑥	FADE	Fade color-changing mode
⑦	SMOOTH	Smooth color-changing mode
⑧	RESET	Reset to default settings
⑨	DIMMER BUTTONS	Adjust the brightness/intensity

IR Remote Operation

The battery for the remote control has already been installed. Remove and discard the clear plastic pull tab before use.

- 1 Turn on the LED Light by pushing the ON button on the remote control
- 2 Select the desired color or the desired effect by pushing the corresponding button on the remote control
- 3 Set the desired brightness using the buttons to increase/decrease the intensity of color
- 4 Push the OFF button to turn off the LED Light

NOTE 1: For best operation, point the IR remote towards the IR receiver (towards power adapter).

NOTE 2: You can use this Light Strip with a timer outlet or smart plug as it will power on into the last used lighting mode.

Changing the remote control battery:

- 1 The battery compartment is located on the narrow side of the remote control, press the release tab inwards and remove the tray
- 2 Remove the empty battery and insert a 3V battery, type CR2025*, with the positive terminal pointing upwards
- 3 Place the battery compartment back in the remote control so it locks in place

* The listed battery type may differ slightly from what is supplied. When replacing the battery, please verify the actual battery size in the remote control.

Customer Service



1 Year Limited Warranty

Scan QR code for warranty information



866-246-2008



customerservice@monsterilluminescence.com

In the event this product becomes defective, please do not return this product to your retailer.

Warning

Changes or modifications not expressly approved by the party responsible for compliance could void the user's warranty or authority to operate the equipment.

FCC Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Radio Frequency Exposure Statement

The device has been evaluated to meet general RF exposure requirements. The device can be used in fixed or mobile condition. The minimum separation distance is 20cm.

Specifications

- light strip length: 16.4ft (5m)
- cable length:
6ft (1.8m) to power supply + 1.5ft (.5m) to plug
- input: 12V 0.42A
- output: 12V 1A
- remote control: 1 x 3V battery, type CR2025*

*The listed battery type may differ slightly from what is supplied. When replacing the battery, please verify the actual size in the remote control.

EN Need the Quick Start Guide in another language?

FR Besoin du guide de démarrage rapide dans une autre langue?

ES ¿Necesita la guía de comienzo rápido en otro idioma?

DE Benötigen Sie die Schnellstartanleitung in einer anderen Sprache?

IT Serve la guida rapida in un'altra lingua?

RU Вам нужно Краткое руководство на другом языке?



scan for manuals

rechercher des guides d'utilisation

buscar los manuales

nach Handbüchern scannen

scansione dei manuali

сканирование для руководств

www.monsterilluminescence.com/manuals/

The illustrated products and specifications may differ slightly from those supplied. The M Monster logo is a registered trademark of Monster, Inc. or its subsidiaries in the U.S. and other countries and are used under license. All other brand names are trademarks of their respective owners. Neither Jem Accessories, Inc. nor Monster, Inc. is affiliated with the respective owners of their trademarks. Licensed and Manufactured by Jem Accessories, Inc. Edison, NJ 08817. Made in China.